

# Quantum Lost and Found

M. Gregoratti\*

*Dip. Mat., Politecnico di Milano, piazza Leonardo da Vinci 32, I-20133 Milano, Italy*

R. F. Werner†

*Inst. Math. Phys., TU-Braunschweig, Mendelssohnstraße 3, D-38106 Braunschweig, Germany*

We consider the problem of correcting the errors incurred from sending classical or quantum information through a noisy quantum environment by schemes using classical information obtained from a measurement on the environment. We give a conditions for quantum or classical information (prepared in a specified input basis  $B$ ) to be corrigible based on a measurement  $M$ . Based on these criteria we give examples of noisy channels such that (1) no information can be corrected by such a scheme (2) for some basis  $B$  there is a correcting measurement  $M$  (3) for all bases  $B$  there is an  $M$  (4) there is a measurement  $M$  which allows perfect correction for all bases  $B$ . The last case is equivalent to the possibility of correcting quantum information, and turns out to be equivalent to the channel allowing a representation as a convex combination of isometric channels. Such channels are doubly stochastic but not conversely.

## I. INTRODUCTION

A fundamental feature of open quantum systems [1] is the possibility of irreversible evolutions, which arise from coupling the system under consideration to an environment, a unitary evolution of the system together with its environment, and a subsequent reduction to the system. In fact, this mechanism for obtaining decoherence is universal, because any irreversible evolution can be obtained from such a scheme. In this sense decoherence always arises from the loss of information to the environment.

Decoherence is, of course, one of the main problems encountered in the realization of quantum information tasks, from quantum cryptography all the way to the quantum computer. It is therefore natural to try to combat decoherence not just by the usual error correcting codes [2, 3] at system level, but by going to the environment, retrieving some of the lost information, and using it to get a more efficient error correction (see for example the “embedded quantum codes” of Alber et. al [4]). One problem with this idea is immediately obvious: in many cases the “environment” is just too big to be controlled sufficiently well to make the necessary measurements. For example, the correction of errors due to spontaneous emission [5] would require to catch all the emitted photons, which seems impossible in many experimental setups. On the other hand, there are experiments (e.g., inside a cavity) where this may become feasible. What a theoretical analysis in abstract terms can do here is to *tell in advance if there is a chance*. That is, if the noisy channel describing the effective evolution of the system is known, can we decide if there exists a suitable measurement on the environment, which finds just the (classical) information needed to restore the system?

It turns out that channels differ very much in this respect, and that the differences are not simply a question of more or less “noise”. In fact, the noisiest channel of all, the completely depolarizing channel, may be corrected perfectly with such a scheme. On the other hand, there are channels not allowing such correction, even if one only wants to transmit classical information.

Our paper is organized as follows: In Section II, we set up the framework and the basic correction scheme, and we prove the basic criteria for the existence of a correction scheme for a given channel, and a given measurement on the environment. In Section II D we describe the degrees of corrigibility, which are then shown by explicit examples to be distinct in Section III. It turns out that qubit channels are more easily shown to be corrigible, which will be shown in Section IV. In real life applications, it will often not be possible to achieve a complete correction of errors. Instead one is interested in the *optimal* correction scheme. One part of this optimization problem is solved in Section V: for fixed measurement on the environment we determine the optimal recovery operation. In the main paper the environment is assumed to be initially in a pure state. Without that assumption corrigibility may be dramatically worse, even for qubits (Section VI). In the final Section VII we remark on an alternative correction scheme, in which there is more classical communication between the system and the ‘Lost and Found Office’ in the environment: if we allow

---

\*Electronic address: gregoratti@mate.polimi.it

†Electronic address: r.werner@tu-bs.de




FIG. 1: The basic correction scheme. The noisy channel  $T$  is represented by the shaded shape, and consists of a unitary coupling  $U$  of the system to an environment in state  $\rho_0$ . The result  $\alpha$  of the measurement  $M$  on the environment is used to select the recovery operation  $R_\alpha$ , resulting in the overall corrected channel  $T_{\text{corr}}$ .

rounds of classical communication and local quantum operations, correction may become possible in some situations, in which our scheme would not work.

## II. GENERAL RESULTS

### A. The correction scheme

In this Section we establish some notation, and describe the general scheme (see Fig. 1) for correcting information using information from the environment. Throughout we will consider a channel  $T$  transforming systems with Hilbert space  $\mathcal{H}_1$  into systems with a possibly different Hilbert space  $\mathcal{H}_2$ . Both Hilbert spaces are assumed to be finite dimensional. We work in the Schrödinger picture, so the channel is given by a map taking each input density operator  $\rho$  on  $\mathcal{H}_1$  to a density operator  $T(\rho)$  on  $\mathcal{H}_2$ . This map extends to a linear mapping  $T : \mathcal{L}(\mathcal{H}_1) \rightarrow \mathcal{L}(\mathcal{H}_2)$ , where  $\mathcal{L}(\mathcal{H})$  denotes the space of all linear operators on a Hilbert space  $\mathcal{H}$ . Of course,  $T$  must be completely positive and trace preserving [2], which is equivalent to the possibility of obtaining it by unitary coupling to an environment. It is natural to distinguish also the Hilbert spaces  $\mathcal{K}_1$  and  $\mathcal{K}_2$  of the environment before and after the coupling. Then the interaction is given by a unitary operator  $U : \mathcal{H}_1 \otimes \mathcal{K}_1 \rightarrow \mathcal{H}_2 \otimes \mathcal{K}_2$ . If the initial states of system and environment are density operators  $\rho$  and  $\rho_0$ , respectively, an observable  $A \in \mathcal{L}(\mathcal{H}_2)$  measured on the system after the interaction has expectation

$$\begin{aligned} \text{tr}(T(\rho)A) &= \text{tr}\left(U(\rho \otimes \rho_0)U^*(A \otimes \mathbb{1})\right), \quad \text{i.e.} \\ T(\rho) &= \text{tr}_{\mathcal{K}_2}\left(U(\rho \otimes \rho_0)U^*\right), \end{aligned} \quad (1)$$

where the trace in the second line is the partial trace over the Hilbert space specified. In this expression we have simply discarded the environment by choosing an observable of the form  $(A \otimes \mathbb{1})$  on the combined system. A measurement on the environment  $\mathcal{K}_2$  would be given by a family of operators  $M_\alpha \in \mathcal{L}(\mathcal{K}_2)$ , indexed by the classical outcomes “ $\alpha$ ”, with  $M_\alpha \geq 0$  and  $\sum_\alpha M_\alpha = \mathbb{1}$ . Inserting  $M_\alpha$  instead of  $\mathbb{1}$  into (1) we get

$$\text{tr}(T_\alpha(\rho)A) = \text{tr}\left(U(\rho \otimes \rho_0)U^*(A \otimes M_\alpha)\right), \quad (2)$$

where the completely positive map  $T_\alpha$  is a selective channel giving the (non-normalized) output state  $T_\alpha(\rho)$  of the subensemble of systems for which the measurement performed after the interaction on the environment has given the result “ $\alpha$ ”: the probability of getting  $\alpha$  is  $\text{tr} T_\alpha(\rho)$ , the normalized output state for the corresponding subensemble is  $T_\alpha(\rho)/\text{tr} T_\alpha(\rho)$ , while  $\text{tr}(T_\alpha(\rho)A)/\text{tr} T_\alpha(\rho)$  is the expectation of  $A$  in that subensemble. The structure of a channel, decomposed into a sum  $T = \sum_\alpha T_\alpha$  of selective operations, is called an *instrument* [1]. It is the general form of a quantum operation yielding classical information (i.e.,  $\alpha$ ) together with a quantum output.

We can now introduce the idea of correction: this will be a restoring operation taking systems with Hilbert space  $\mathcal{H}_2$  to systems with the same Hilbert space  $\mathcal{H}_1$  as the inputs. We allow this operation to depend in an arbitrary way on the available classical information  $\alpha$ . Hence it is given by a family of channels  $R_\alpha : \mathcal{L}(\mathcal{H}_2) \rightarrow \mathcal{L}(\mathcal{H}_1)$ . After correction, the state of the subensemble for which the measurement has given the result  $\alpha$ , will be  $R_\alpha(T_\alpha(\rho))$  up to the normalization factor  $\text{tr}(T_\alpha(\rho))$ . The overall corrected channel is built from these conditional operations by

ignoring the intermediate information  $\alpha$ , and is the sum of these contributions:

$$T_{\text{corr}} = \sum_{\alpha} R_{\alpha} \circ T_{\alpha} : \mathcal{L}(\mathcal{H}_1) \rightarrow \mathcal{L}(\mathcal{H}_1) , \quad (3)$$

where  $\circ$  means composition of maps. We will say that the scheme *restores quantum information*, if the corrected channel is the ideal channel on  $\mathcal{H}_1$ , i.e.,

$$T_{\text{corr}} = \text{id}_1 .$$

By the “No information without perturbation” Theorem, this condition is equivalent to  $R_{\alpha} \circ T_{\alpha} = c_{\alpha} \text{id}_1$ , for some  $c_{\alpha} \geq 0$ ,  $\sum_{\alpha} c_{\alpha} = 1$ . This implies firstly that we get the result  $\alpha$  with probability  $\text{tr}(T_{\alpha}(\rho)) = \text{tr}(R_{\alpha}(T_{\alpha}(\rho))) = c_{\alpha}$ , which is independent of  $\rho$ . That is, the results  $\alpha$  contain no information whatsoever about the initial state. Moreover, this special form implies that the original quantum state is restored, not only for the whole ensemble, but also for each subensemble selected according to the result  $\alpha$ .

We will also consider in detail the question if classical information can be transmitted faithfully. In this case we use a particular basis  $B$  in the input space  $\mathcal{H}_1$  to encode the information. Let  $B_x$ ,  $x = 1, \dots, \dim \mathcal{H}_1$ , denote the one-dimensional projections onto the basis vectors. Then we will say that the scheme *restores classical information in basis  $B$* , if

$$T_{\text{corr}}(B_x) = B_x . \quad (4)$$

Now condition (4) is equivalent to  $R_{\alpha} \circ T_{\alpha}(B_x) = B_x \cdot \text{tr} T_{\alpha}(\rho)$  and again we can say that also for each  $\alpha$ -subensemble classical information is restored.

## B. Independence of Coupling

Whether or not we can find a correction scheme in principle depends not just on the noisy channel  $T$ , but on the particular way in which it is realized by coupling, i.e., on the unitary interaction  $U$  and the initial state  $\rho_0$  of the environment. However, if  $\rho_0$  happens to be a pure state this dependence simplifies considerably. It is clear from (3) that environments in which the same decompositions  $T = \sum_{\alpha} T_{\alpha}$  of a given channel  $T$  can be realized are completely equivalent in terms of retrieval of lost information in our scheme. And it is equally clear that, if we can further decompose some  $T_{\alpha} = T_{\alpha'} + T_{\alpha''}$ , we strictly improve our chances for correction: we can always choose the same recovery operation  $R_{\alpha'} = R_{\alpha''} = R_{\alpha}$  reproducing the previous result, but it might be helpful to take  $R_{\alpha'} \neq R_{\alpha''}$  instead. In this sense the following Theorem tells us that all realizations of a channel  $T$  by coupling to an *initially pure* environment are equivalent and that for all of them there are no limitations in the choice of the decomposition.

Assuming a pure environment may seem counterintuitive, if the environment is seen as that “large and uncontrolled system out there”. However, in situations in which our correction scheme might be applied, a good control of the environment is needed anyhow. The “environment” is then only that part with which the system is in contact, and which together with the system is sufficiently well isolated from the rest of the world. As the following Theorem and Section VI show, if we want to “tell in advance if there is a chance”, without using information about the details of the coupling, we should make this assumption in any case.

Pure environments are also in keeping with the general idea that all decoherence arises from coupling to an environment. Only with a pure environment we can separate the combined effects of interaction and tracing out on the one hand, from the transfer of impure information from the environment to the system on the other. Not that this is an absolute distinction: by purifying the environment, i.e., by considering it as a subsystem of a larger system in a pure state, we can always represent the ‘transfer of impurity’ as a dynamical coupling to one part of a pure entangled system.

Before stating and proving the Theorem, let us recall some basic facts about possible decompositions and refinements of a given channel  $T$ . The finest, i.e., the most informative measurements are those for which the decomposition  $T = \sum_{\alpha} T_{\alpha}$  allows no proper refinement. This means that the only further decompositions of  $T_{\alpha} = T_{\alpha'} + T_{\alpha''}$  into completely positive terms have  $T_{\alpha'}$  and  $T_{\alpha''}$  proportional to  $T_{\alpha}$ . This is equivalent to  $T_{\alpha}(\rho) = t_{\alpha} \rho t_{\alpha}^*$  for some operator  $t_{\alpha} : \mathcal{H}_1 \rightarrow \mathcal{H}_2$ , i.e.,  $T_{\alpha}$  is a single Kraus summand in a Kraus representation

$$T(\rho) = \sum_{\alpha} t_{\alpha} \rho t_{\alpha}^* , \quad \sum_{\alpha} t_{\alpha}^* t_{\alpha} = \mathbb{1} . \quad (5)$$

Such a representation is *not* unique, and we will see examples later in which the proper choice of the  $t_{\alpha}$  is essential. However, it is easy to see that different Kraus representations are related by [2, Theorem 8.2]

$$t_{\alpha} = \sum_{\beta} u_{\alpha\beta} s_{\beta} , \quad (6)$$

where the two sets of Kraus operators  $t_\alpha$  and  $s_\beta$  have been brought to the same length by appending zeros, and  $u$  is a unitary matrix. Therefore non-refinable decompositions are given by Kraus representations and all the others can be obtained by grouping some terms in some Kraus representation.

Finally, as announced, we prove that all realizations of a given channel with an initially pure environment are equivalent, because every decomposition of the channel can be realized by a measurement on the environment. Except for Section VI we will assume from now on that the environment is initially pure.

**Theorem 1** *Let  $U : \mathcal{H}_1 \otimes \mathcal{K}_1 \rightarrow \mathcal{H}_2 \otimes \mathcal{K}_2$  be a unitary operator, let  $\rho_0 = |\Psi_0\rangle\langle\Psi_0| \in \mathcal{L}(\mathcal{K}_1)$  be a pure state and let  $T$  be the channel (1). Then every decomposition of the channel  $T = \sum_\alpha T_\alpha$  with  $T_\alpha$  completely positive can be realized in the form (2) by choosing a suitable observable  $M_\alpha$  on  $\mathcal{K}_2$ .*

*Proof.* It is sufficient to prove the Theorem for a Kraus decomposition (5) because, if  $T_\alpha$  are sums of Kraus terms, we simply have to find the observable for the refined Kraus decomposition and then sum the corresponding terms.

Given a decomposition  $T(\rho) = \sum_\alpha T_\alpha(\rho) = \sum_\alpha t_\alpha \rho t_\alpha^*$ , let us find the observable  $M_\alpha$ . Take an arbitrary complete system  $\{\chi_\beta\}$  in  $\mathcal{K}_2$  (i.e., not necessarily normalized vectors such that  $\sum_\beta |\chi_\beta\rangle\langle\chi_\beta| = \mathbb{1}$ ). Then the corresponding observable  $F_\beta = |\chi_\beta\rangle\langle\chi_\beta|$  inserted in (2) gives the Kraus decomposition of the channel  $T(\rho) = \sum_\beta S_\beta(\rho) = \sum_\beta s_\beta \rho s_\beta^*$ , where  $\langle\psi, s_\beta \varphi\rangle = \langle\psi \otimes \chi_\beta, U \varphi \otimes \Psi_0\rangle$ . Indeed

$$\langle\psi_1, S_\beta(|\varphi_1\rangle\langle\varphi_2|) \psi_2\rangle = \langle U \varphi_2 \otimes \Psi_0, \psi_2 \otimes \chi_\beta \rangle \langle\psi_1 \otimes \chi_\beta, U \varphi_1 \otimes \Psi_0\rangle = \langle\psi_1, s_\beta |\varphi_1\rangle\langle\varphi_2| s_\beta^* \psi_2\rangle.$$

Since  $t_\alpha$  and  $s_\beta$  are Kraus operators of a same channel  $T$ , there exists a unitary matrix  $u$  such that (6) holds. Then also  $\mu_\alpha = \sum_\beta \bar{u}_{\alpha\beta} \chi_\beta$  is a complete system in  $\mathcal{K}_2$  and  $M_\alpha = |\mu_\alpha\rangle\langle\mu_\alpha|$  is the required observable:

$$\begin{aligned} \text{tr}\left(U(|\varphi_1\rangle\langle\varphi_2| \otimes \rho_0) U^*(|\psi_2\rangle\langle\psi_1| \otimes M_\alpha)\right) &= \sum_{\beta,\gamma} \langle U \varphi_2 \otimes \Psi_0, \psi_2 \otimes \bar{u}_{\alpha\beta} \chi_\beta \rangle \langle\psi_1 \otimes \bar{u}_{\alpha\gamma} \chi_\gamma, U \varphi_1 \otimes \Psi_0\rangle \\ &= \sum_{\beta,\gamma} \bar{u}_{\alpha\beta} u_{\alpha\gamma} \langle\psi_1, s_\gamma |\varphi_1\rangle\langle\varphi_2| s_\beta^* \psi_2\rangle = \langle\psi_1, t_\alpha |\varphi_1\rangle\langle\varphi_2| t_\alpha^* \psi_2\rangle. \end{aligned}$$

□

Since we assume pure  $\rho_0$  in the sequel, “choosing a measurement  $M$  on the environment” is synonymous with “choosing a decomposition of the channel into completely positive summands”, and keeping in mind the task to decide the existence of correction scheme, we will always consider Kraus decompositions.

### C. The Basic Criteria for Correction

Before classifying channels according to the existence of a correction scheme restoring quantum or classical information, we establish criteria to say if a certain measurement on the environment, i.e. a certain Kraus decomposition of the channel, allows such restoring. For both kinds of information we find simple necessary and sufficient conditions based on the operators  $t_\alpha^* t_\alpha$ .

#### 1. Criterion for Quantum Information

**Proposition 2** *Let  $T : \mathcal{L}(\mathcal{H}_1) \rightarrow \mathcal{L}(\mathcal{H}_2)$  be a channel. Then, for a given Kraus decomposition  $T(\rho) = \sum_\alpha t_\alpha \rho t_\alpha^*$ , there exists a family of channels  $R_\alpha : \mathcal{L}(\mathcal{H}_2) \rightarrow \mathcal{L}(\mathcal{H}_1)$  restoring quantum information if and only if  $t_\alpha^* t_\alpha = c_\alpha \mathbb{1}$  for all  $\alpha$ , with  $c_\alpha \geq 0$ ,  $\sum_\alpha c_\alpha = 1$ .*

*Proof.* Both directions are simple. As noted in Section II A, the existence of the  $R_\alpha$  requires that  $c_\alpha = \text{tr}(T_\alpha(\rho)) = \text{tr}(t_\alpha^* t_\alpha \rho)$  for all  $\rho$ , and hence  $t_\alpha^* t_\alpha = c_\alpha \mathbb{1}$ .

For the converse, suppose that the last equation holds. Then  $t_\alpha = \sqrt{c_\alpha} v_\alpha$ , with  $v_\alpha : \mathcal{H}_1 \rightarrow \mathcal{H}_2$  an isometry, and we can define the restoring channels

$$R_\alpha(\rho') = v_\alpha^* \rho' v_\alpha + \rho_\alpha \text{tr}\left(\rho'(\mathbb{1} - v_\alpha v_\alpha^*)\right), \quad (7)$$

where  $\rho_\alpha$  are arbitrary density operators in  $\mathcal{L}(\mathcal{H}_1)$ .

□

The structure of the correction scheme in Proposition 2 is very clear when  $\mathcal{H}_1 = \mathcal{H}_2$ , so that  $v_\alpha$  are unitary and the second term in (7) vanishes. The measurement on the environment decomposes  $T$  into a convex combination of unitary channels,  $T(\rho) = \sum_\alpha c_\alpha v_\alpha \rho v_\alpha^*$ , transforming a quantum system with one of the reversible evolutions  $\rho \mapsto v_\alpha \rho v_\alpha^*$ , which occur randomly with probability  $c_\alpha$ . The measurement detects the transformation occurred and  $R_\alpha(\rho') = v_\alpha^* \rho' v_\alpha$  restores the initial state  $\rho$ . When  $\dim \mathcal{H}_2 > \dim \mathcal{H}_1$ , the operators  $v_\alpha$  are isometries,  $\rho \mapsto v_\alpha \rho v_\alpha^*$  still describes a reversible transformation and the structure of the correction scheme is similar. The channel is decomposed into a convex combination of isometric channels transforming a quantum system with state  $\rho \in \mathcal{L}(\mathcal{H}_1)$  into a quantum system with one of the states  $v_\alpha \rho v_\alpha^* \in \mathcal{L}(\mathcal{H}_2)$ , which occur randomly with probability  $c_\alpha$ . Once  $\alpha$  is observed, the corresponding  $R_\alpha$  (7) restores  $\rho$ . Note that we are interested in applying  $R_\alpha$  only to states  $\rho' = v_\alpha \rho v_\alpha^*$  for which the second term in (7) vanishes, but we have to introduce such a term to get a trace preserving  $R_\alpha$ .

When  $\dim \mathcal{H}_1 = \dim \mathcal{H}_2 = N$ , the Proposition yields an interesting necessary condition for corrigibility: since each  $t_\alpha$  is proportional to a unitary, the completely chaotic state  $\bar{\rho} = N^{-1}\mathbb{1}$  is mapped by the channel to  $T(\bar{\rho}) = N^{-1} \sum_\alpha t_\alpha t_\alpha^* = N^{-1} \sum_\alpha c_\alpha = N^{-1}\mathbb{1} = \bar{\rho}$ . Channels with  $\dim \mathcal{H}_1 = \dim \mathcal{H}_2$  and

$$T(\mathbb{1}) = \mathbb{1} \quad (8)$$

are called *doubly stochastic* because this is the exact analog of a well known property of transition probability matrices: such a matrix is called doubly stochastic if the chaotic (equi-)distribution is invariant, which is to say that both rows and columns add up to 1. A famous Theorem by Birkhoff then states that every doubly stochastic matrix is a convex combination of permutation operators, which in turn would translate to “reversible transition matrix”, or “unitarily implemented channels” in the quantum case. In other words, Birkhoff’s Theorem would suggest by analogy that double stochasticity is not only necessary but even sufficient for the conditions of the Proposition. However, the quantum analog of Birkhoff’s Theorem fails. This was shown in [6], to which we refer for more background and results. Even for channels close to the identity one can find doubly stochastic channels, which are not convex combination of unitary ones [7]. It turns out that the main counterexample of [6] for  $d = 3$  is also needed in our paper (see Example 4). For  $d = 2$ , the quantum analog of Birkhoff’s Theorem holds [6], and we give a direct proof of this fact in Section IV B.

## 2. Criterion for Classical Information

**Theorem 3** *Let  $T : \mathcal{L}(\mathcal{H}_1) \rightarrow \mathcal{L}(\mathcal{H}_2)$  be a channel. Then, for a given basis  $B$  in  $\mathcal{H}_1$  and a given Kraus decomposition  $T(\rho) = \sum_\alpha t_\alpha \rho t_\alpha^*$ , there exists a family of channels  $R_\alpha : \mathcal{L}(\mathcal{H}_2) \rightarrow \mathcal{L}(\mathcal{H}_1)$  restoring classical information in basis  $B$  if and only if  $t_\alpha^* t_\alpha$  are all diagonal in  $B$ .*

*Proof.* If  $T$  is used to send classical information encoded on  $B$ , then the initial state is one of the  $B_x$  and, when the measurement on the environment gives  $\alpha$ , the (non normalized) output state is one of the non zero  $t_\alpha B_x t_\alpha^*$ . Therefore it is clear that a restoring channel  $R_\alpha$  exists if and only if  $t_\alpha B_x t_\alpha^*$  are orthogonal. Indeed, if  $R_\alpha$  exists, the possible  $t_\alpha B_x t_\alpha^*$  have to be orthogonal because they can be perfectly distinguished, e.g. by a measurement of  $B$  after the application of  $R_\alpha$ , while, if the  $t_\alpha B_x t_\alpha^*$  are orthogonal, a measurement can distinguish them and we could obtain  $R_\alpha$  by measuring and reparing. In this case we would employ restoring channels of the kind

$$R_\alpha(\rho') = \sum_x' |\varphi_x\rangle \langle \psi_x^{(\alpha)} | \rho' | \psi_x^{(\alpha)} \rangle \langle \varphi_x | + E_{(\alpha)} \rho' E_{(\alpha)} , \quad (9)$$

where  $\varphi_x$  are the vectors in the basis  $B$ , the sum is over those  $x$  such that  $\|t_\alpha \varphi_x\| \neq 0$ , while  $\psi_x^{(\alpha)} = t_\alpha \varphi_x / \|t_\alpha \varphi_x\|$  and  $E_{(\alpha)}$  is the orthogonal projection on  $\{t_\alpha \varphi_x \mid x = 1, \dots, \dim \mathcal{H}_1\}^\perp$ .

Finally it is clear that  $t_\alpha B_x t_\alpha^*$  are orthogonal, i.e.

$$t_\alpha |\varphi_x\rangle \langle \varphi_x | t_\alpha^* t_\alpha |\varphi_y\rangle \langle \varphi_y | t_\alpha^* = 0 , \quad \forall x \neq y ,$$

if and only if  $\langle \varphi_x, t_\alpha^* t_\alpha \varphi_y \rangle = 0$  for all  $x \neq y$ , i.e.  $t_\alpha^* t_\alpha$  is diagonal in  $B$ . □

Let us remark that (9) is not the only possible choice of  $R_\alpha$ : given a Kraus decomposition of  $T$ , in Section V, eq. (17) and (20), we will find a generalization of channels (7) which could restore classical information as well as channels (9), but which would also give a correction scheme allowing optimal recovery of quantum information if this were sent through the channel.

### D. Classification of Examples

In this section we summarize the properties to be investigated in the coming Section.

**Definiton 4** Consider a channel  $T$ , realized by coupling to an environment. We call it

- a ‘Q’ channel, if QUANTUM information can be corrected, i.e., the conditions of Proposition 2 hold.
- a ‘DS’ channel, if it is DOUBLY STOCHASTIC (cf. Eq. (8)).
- a ‘A’ channel, if for ALL bases  $B$  a correction scheme exists (i.e., the conditions of Theorem 3 hold).
- a ‘S’ channel, if for SOME basis  $B$  a correction scheme exists.
- a ‘N’ channel, if NONE of the above properties is asserted.

The somewhat strange category ‘N’ is needed to make the implication ‘S’ $\Rightarrow$ ‘N’ trivial, and hence to get the hierarchy in the following theorem. It is understood that the implications involving ‘DS’ only make sense when  $\dim \mathcal{H}_1 = \dim \mathcal{H}_2$ . The examples of the next section together constitute a proof of the following Theorem:

**Theorem 5** All implications

$$'DS' \Leftarrow 'Q' \Rightarrow 'A' \Rightarrow 'S' \Rightarrow 'N' \quad (10)$$

are strict in general. However, for qubit channels ( $\dim \mathcal{H}_1 = 2$ ), we have the implications

$$'DS' \Leftrightarrow 'Q' \Rightarrow 'A' \Leftrightarrow 'S' \Leftrightarrow 'N' \quad (11)$$

## III. EXAMPLES

### A. ‘Q’ Channels

Let us start with two remarkable examples of channels, which are known to destroy all quantum information and for which no ordinary quantum error correcting code works. Nevertheless they turn out to be channels of type ‘Q’, so that quantum information can be completely restored with the help of a suitable measurement on the environment.

**Example 1.** Overall state change associated with a von Neumann measurement. Take  $\mathcal{H}_1 = \mathcal{H}_2$  to be  $N$ -dimensional, choose a basis  $B$  and consider, as above, the one dimensional projections  $B_\alpha$  to the basis vectors. The complete von Neumann measurement associated to this basis results in the channel

$$T(\rho) = \sum_{\beta=1}^N B_\beta \rho B_\beta .$$

Obviously, the  $B_\beta$  are diagonal only in the basis  $B$  itself, so this is the unique basis in which classical information can be sent and corrected for this particular measurement (Kraus decomposition of  $T$ ). However, we can also represent  $T$  as

$$T(\rho) = \sum_{\alpha=1}^N t_\alpha \rho t_\alpha , \quad t_\alpha = \sum_{\beta=1}^N \frac{1}{\sqrt{N}} e^{\frac{2\pi i}{N} \alpha \beta} B_\beta = \frac{1}{\sqrt{N}} V_\alpha ,$$

where all the  $V_\alpha$  are unitary. Hence  $T$  is a ‘Q’ channel.

This channel has quantum channel capacity zero [3], but classical capacity  $\log_2(N)$ . The following channel is even worse: without help from the environment it allows no information transmission at all.

**Example 2.** Depolarising channel.

Take  $\mathcal{H}_1 = \mathcal{H}_2$  with  $\dim \mathcal{H}_1 = N$ . Then the depolarising channel is defined by  $T(\rho) = \frac{1}{N} \mathbb{1}$ . It is a ‘Q’ channel because it admits the Kraus representation

$$T(\rho) = \sum_{j,k=1}^N t_{j,k} \rho t_{j,k}^* , \quad t_{j,k} = \frac{1}{N} \sum_{x=1}^N e^{\frac{2\pi i}{N} x k} |x+j\rangle \langle x| = \frac{1}{N} v_{j,k} ,$$

with unitary operators  $v_{j,k}$ , where  $\{|x\rangle\}_{x \in \mathbb{Z}_N}$  denotes a basis labeled cyclically so that addition in  $|x+j\rangle$  is modulo  $N$ . The representations of the depolarizing channel with Kraus operators proportional to unitaries, of which there are very many for larger  $N$ , are in fact, in one-to-one correspondence to quantum teleportation schemes and superdense coding schemes [8].

**Casimir channel.** The next example and some of the following belong to a family we call Casimir channels. These can be defined starting from any compact Lie group. Let us recall that all irreducible unitary representations  $\pi$  of such a group live in finite dimensional Hilbert spaces  $\mathcal{H}_\pi$  and that its Lie algebra admits an invariant positive definite quadratic form  $g$  [9]. Then it is easy to define a channel with input and output spaces equal to  $\mathcal{H}_\pi$ : if  $L_\alpha$  denote the generators of the Lie algebra and if we consider the invariant quadratic polynomial  $\sum_{\alpha,\beta} g_{\alpha\beta} L_\alpha L_\beta$  (second order Casimir operator), then  $\sum_{\alpha,\beta} g_{\alpha\beta} \pi(L_\alpha) \pi(L_\beta) = \lambda_\pi \mathbb{1}$ , because this operator commutes with the group representation, and  $\pi$  is irreducible. We use here the convention that  $\pi(L)$  denotes the self-adjoint (rather than skew-adjoint) generators of the group in the representation  $\pi$ . Then  $\lambda_\pi > 0$ , and the map

$$T(\rho) = \sum_{\alpha,\beta} \frac{1}{\lambda_\pi} g_{\alpha\beta} \pi(L_\alpha) \rho \pi(L_\beta)$$

defines automatically a channel, which is completely positive because we could choose generators  $L_\alpha$  diagonalizing  $g$  and hence giving directly a Kraus representation of  $T$ . Note that this is always a ‘DS’ channel because the latter Kraus operators are self-adjoint.

In examples 3, 4 and 6 we consider Casimir channels associated with irreducible representations of  $SU_2$ , with  $g_{\alpha\beta} = \delta_{\alpha\beta}$  and  $J_\alpha = \pi(L_\alpha)$  equal to the angular momentum operators generating a spin- $s$  representation of  $SU_2$  on  $\mathcal{H}$ ,  $\dim \mathcal{H} = 2s + 1$ . Then  $\sum_\alpha J_\alpha^2 = s(s+1) \mathbb{1}$  and the channel is

$$T(\rho) = \sum_{\alpha=1}^3 \frac{1}{s(s+1)} J_\alpha \rho J_\alpha. \quad (12)$$

**Example 3.** *Casimir channel,  $s = 1/2$ .* Take  $\mathcal{H}_1 = \mathcal{H}_2 = \mathbb{C}^2$ , and use the Pauli spin operators  $\pi(L_\alpha) = \frac{1}{2} \sigma_\alpha$  as generators of the spin- $\frac{1}{2}$  representation of  $SU_2$ . This gives the Casimir channel ( $\lambda_\pi = \frac{1}{2}(\frac{1}{2} + 1) = \frac{3}{4}$ )

$$T(\rho) = \sum_{\alpha=1}^3 \frac{1}{3} \sigma_\alpha \rho \sigma_\alpha = \frac{2}{3} \mathbb{1} - \frac{1}{3} \rho,$$

which is a ‘Q’ channel because the Pauli matrices  $\sigma_\alpha$  are unitary. This is the best completely positive approximation to the “Universal Not” operation, which would take any pure state on  $\mathbb{C}^2$  to its orthogonal complement [11].

## B. ‘A not Q’ Channels

We give two examples of ‘A not Q’ channels. Example 4 is ‘DS’, and hence also a counterexample to the quantum analog of Birkhoff’s Theorem. Example 5 is not ‘DS’, so property ‘Q’ may fail in different ways.

**Example 4.** *Casimir channel,  $s = 1$ .* This representation is just the orthogonal group in 3 dimensions. Hence we take  $\mathcal{H}_1 = \mathcal{H}_2 = \mathbb{C}^3$  and, with a basis  $\{|x\rangle\}_{x=1}^3$ , we can write

$$T(\rho) = \sum_{\beta=1}^3 \frac{1}{2} J_\beta \rho J_\beta, \quad \langle i | J_\beta | j \rangle = i \varepsilon_{ij\beta},$$

where  $\varepsilon_{ij\beta}$  is the completely antisymmetric tensor and  $J_\beta$  are the angular momentum operators in spin-1 representation. This channel was already used as a counterexample to the quantum analog of Birkhoff’s Theorem in [6], but also to a completely different problem in [10].

Since the  $J_\beta$  are antisymmetric, the same will be true for any choice of Kraus operators, which must be of the form  $t_\alpha = \sum_\beta u_{\alpha\beta} J_\beta / \sqrt{2}$  by eq. (6). But in odd dimension an antisymmetric matrix necessarily has determinant zero, and hence cannot be unitary. It follows that  $T$  is not a ‘Q’ channel. On the other hand, like every Casimir channel,  $T$  enjoys property ‘DS’.

It remains to show that  $T$  is an ‘A’ channel. Note that the  $J_\alpha^2$  are diagonal, so it is obvious that correction works for the standard basis and, by  $SU_2$  invariance, for all bases arising from this by orthogonal (*real* unitary) transformation.

But consider an arbitrary orthonormal basis  $\{\varphi_y\}_{y=1}^3$ . Then we can take the unitary matrix rotating the standard basis to  $\{\varphi_y\}$  also as the matrix transforming the Kraus operators. Then

$$T(\rho) = \sum_{\alpha} t_{\alpha} \rho t_{\alpha}^*, \quad t_{\alpha} = \sum_{\beta} \langle \varphi_{\alpha} | \beta \rangle \frac{1}{\sqrt{2}} J_{\beta}.$$

Using the properties  $J_{\beta}^2 = \mathbb{1} - |\beta\rangle\langle\beta|$  and, for  $\beta \neq \gamma$ ,  $J_{\beta}J_{\gamma} = -|\gamma\rangle\langle\beta|$ , it is easy to verify that

$$t_{\alpha}^* t_{\alpha} = \frac{1}{2} (\mathbb{1} - |\varphi_{\alpha}\rangle\langle\varphi_{\alpha}|).$$

Since these operators are diagonal w.r.t.  $\{\varphi_y\}$ ,  $T$  is an ‘A’ channel.

**Example 5.** *Collapsing channel*

Let  $\dim \mathcal{H}_1 > 1$ , fix an arbitrary unit vector  $\psi$  in  $\mathcal{H}_2$  and define the channel

$$T(\rho) = |\psi\rangle\langle\psi|.$$

Then  $T$  is not a ‘Q’ channel because every Kraus operator  $t_{\alpha}$  necessarily has rank 1, and of course, if  $\dim \mathcal{H}_1 = \dim \mathcal{H}_2$ , it is neither a ‘DS’ channel. Anyway it is always an ‘A’ channel. Indeed for every basis  $\{\varphi_x\}$  in  $\mathcal{H}_1$  we have the Kraus representation

$$T(\rho) = \sum_{\alpha} t_{\alpha} \rho t_{\alpha}^* = \sum_{\alpha} |\psi\rangle\langle\varphi_{\alpha}| \rho |\varphi_{\alpha}\rangle\langle\psi|,$$

where all  $t_{\alpha}^* t_{\alpha} = |\varphi_{\alpha}\rangle\langle\varphi_{\alpha}|$  are diagonal w.r.t.  $\{\varphi_x\}$ .

### C. ‘S not A’ Channels

**Example 6.** *Casimir channel*,  $s = 3/2$ . We show first that *every*  $SU_2$ -Casimir channel is an ‘S’ channel. Indeed, we can rewrite the channel (12) in the Kraus representation

$$T(\rho) = \sum_{\alpha=1}^3 t_{\alpha} \rho t_{\alpha}^*, \quad t_1 = \frac{J_1 + iJ_2}{\sqrt{2s(s+1)}} = \frac{J_+}{\sqrt{2s(s+1)}}, \quad t_2 = \frac{J_1 - iJ_2}{\sqrt{2s(s+1)}} = \frac{J_-}{\sqrt{2s(s+1)}}, \quad t_3 = \frac{J_3}{\sqrt{s(s+1)}},$$

where

$$t_1^* t_1 = \frac{1}{2s(s+1)} J_- J_+, \quad t_2^* t_2 = \frac{1}{2s(s+1)} J_+ J_-, \quad t_3^* t_3 = \frac{1}{s(s+1)} J_3^2$$

are all diagonal w.r.t. the eigenbasis of  $J_3$ .

On the other hand, the channel with  $s = 3/2$  is not of type ‘A’, because there is no non-zero linear combination  $t = xJ_1 + yJ_2 + zJ_3$  such that  $t^* t$  is diagonal w.r.t. the basis

$$\begin{aligned} \varphi_1 &= (|3/2\rangle + i|1/2\rangle)/\sqrt{2}, \\ \varphi_2 &= (|3/2\rangle - i|1/2\rangle)/\sqrt{2}, \\ \varphi_3 &= |-1/2\rangle, \\ \varphi_4 &= |-3/2\rangle, \end{aligned}$$

where  $|m\rangle$  denotes the eigenstates of  $J_3$ .

Let us note that examples 5 and 6 together show that there is no logical relation between properties ‘A’ and ‘DS’.

### D. ‘N not S’ Channels

**Example 7.** In order to exhibit a channel  $T$  without even property ‘S’, we construct Kraus operators  $t_{\alpha} : \mathcal{H} \rightarrow \mathcal{H}$ ,  $\alpha = 1, \dots, 3$ , such that

$$\left[ \left| \sum_{\alpha} \xi_{\alpha} t_{\alpha} \right|^2, \left| \sum_{\alpha} \zeta_{\alpha} t_{\alpha} \right|^2 \right] = 0 \quad (13)$$



implies linear dependence of the vectors  $\xi$  and  $\zeta$ . Then no matter how we recombine the Kraus operators  $t_\alpha$  according to eq. (6), we cannot make even two (let alone all)  $s_\alpha^* s_\alpha$  commute, so they cannot be jointly diagonal in any basis.

The idea of the construction is to take the Kraus operators as direct sums  $t_\alpha = \bigoplus_{i=0}^N t_\alpha^{(i)}$  such that for every  $i$ , the  $t_\alpha^{(i)}$  are Kraus operators in their own right. Then eq. (13) becomes

$$\bigoplus_{i=0}^N \left[ \left| \sum_{\alpha} \xi_{\alpha} t_{\alpha}^{(i)} \right|^2, \left| \sum_{\alpha} \zeta_{\alpha} t_{\alpha}^{(i)} \right|^2 \right] = 0.$$

This holds if and only if (13) holds for every summand. Hence we can increase the demands on  $\xi$  and  $\zeta$  by adding more and more terms to the direct sum, up to leaving only the obvious solution  $\xi \propto \zeta$ .

It is convenient to choose one summand as  $t_{\alpha}^{(0)} = |\psi\rangle\langle\alpha|$ , where  $\psi \in \mathbb{C}^3$  is an arbitrary unit vector, and the  $|\alpha\rangle$  are a basis in  $\mathbb{C}^3$ . For this choice  $\sum_{\alpha} \xi_{\alpha} t_{\alpha} = |\psi\rangle\langle\xi|$ , where  $\xi$  denotes the vector with the complex conjugate components. Then the commutator (13) becomes  $[\langle\xi|\langle\xi|, |\zeta\rangle\langle\zeta|]$ , which vanishes iff  $\xi$  and  $\zeta$  are either linearly dependent or orthogonal.

We therefore consider the following set of vector pairs in  $\mathbb{C}^3 \times \mathbb{C}^3$ :

$$\mathcal{M} = \left\{ (\xi, \zeta) \in \mathbb{C}^3 \times \mathbb{C}^3 \mid \langle\xi, \zeta\rangle = 0, \|\xi\| = \|\zeta\| = 1 \right\}.$$

Our problem is reduced to showing that there is a finite collection of Kraus operators  $\{t_{\alpha}^{(i)}\}$ ,  $i = 1, \dots, N$  such that the commutators (13) do not vanish simultaneously at the same point in  $\mathcal{M}$ .

It is easy to see that for any pair  $(\xi, \zeta) \in \mathcal{M}$  we can find Kraus operators  $\tilde{t}_{\alpha}$  for which the commutator is non-zero. For example we can pick a  $3 \times 3$  unitary matrix  $u$  whose first two rows are  $\xi$  and  $\zeta$ , and set  $\tilde{t}_{\alpha} = \sum_{\beta} \bar{u}_{\beta\alpha} \frac{2}{\sqrt{15}} J_{\beta}$ , where  $J_{\beta}$  are the angular momentum operators in spin-3/2 representation, so getting  $\sum_{\alpha} \xi_{\alpha} \tilde{t}_{\alpha} = J_1$  and  $\sum_{\alpha} \zeta_{\alpha} \tilde{t}_{\alpha} = J_2$ . Once we have found  $\tilde{t}_{\alpha}$  giving non zero commutator for a certain pair  $(\xi, \zeta)$ , the same operators will work for all  $(\xi', \zeta')$  in a small open neighbourhood of  $(\xi, \zeta)$ . But from this open covering of the compact set  $\mathcal{M}$  we can select a finite subcover, and the corresponding Kraus operators form the desired direct sum channel.

Of course, this construction is non-constructive in the sense that we get no bound on the dimension of the Hilbert space  $\mathcal{H}$ . A more explicit example, perhaps in 3 dimensions with 3 Kraus operators would clearly be preferable.

#### IV. QUBIT CHANNELS

As stated in Theorem 5, qubit channels are special from the point of view of our classification because they enjoy at least property ‘A’ and because double stochasticity becomes equivalent to property ‘Q’. We are now going to prove these results.

##### A. ‘N’ $\Rightarrow$ ‘A’

Here we have to establish property ‘A’ for all qubit channels  $T : \mathcal{L}(\mathcal{H}_1) \rightarrow \mathcal{L}(\mathcal{H}_2)$  with  $\mathcal{H}_1 = \mathbb{C}^2$  the two dimensional Hilbert space. So consider an arbitrary basis of  $\mathcal{H}_1$ , which we can take to be  $\{|0\rangle, |1\rangle\}$ . We have to show that there exist a Kraus representation  $T(\rho) = \sum_{\alpha} t_{\alpha} \rho t_{\alpha}^*$  of the channel  $T$  such that  $t_{\alpha}^* t_{\alpha}$  are all diagonal, i.e. such that  $\langle 0 | t_{\alpha}^* t_{\alpha} | 1 \rangle = 0$  for all  $\alpha$ .

We assume that the arbitrary channel  $T$  has Kraus representation  $T(\rho) = \sum_{\beta} s_{\beta} \rho s_{\beta}^*$ . Clearly then  $\langle 0 | s_{\beta}^* s_{\beta} | 1 \rangle$  does not need to vanish, but  $\sum_{\beta} \langle 0 | s_{\beta}^* s_{\beta} | 1 \rangle = \langle 0 | \mathbb{1} | 1 \rangle = 0$ . Therefore, if we introduce the matrix  $X_{\alpha\beta} = \langle 0 | s_{\alpha}^* s_{\beta} | 1 \rangle$ , it has  $\text{tr}(X) = 0$ . Rotating the Kraus operators by a unitary matrix  $u$  (cf. (6)) is the same as transforming  $X \mapsto \bar{u} X u^*$ . What we want to achieve is to make the diagonal of  $\bar{u} X u^*$  vanish identically. That we can always find such a unitary transformation is the content of the following Lemma.

**Lemma 6** *Let  $X$  be an operator on a finite dimensional Hilbert space  $\mathcal{H}$  with  $\text{tr} X = 0$ . Then there is an orthonormal basis  $\{e_{\alpha}\}$  such that  $\langle e_{\alpha}, X e_{\alpha} \rangle = 0$  for all  $\alpha$ .*

This lemma already appeared in [12] for  $\dim \mathcal{H} = 2^k$ , but we need it for arbitrary  $\dim \mathcal{H} = N$ , and our proof is rather different.

*Proof.* It is sufficient to show that there exists a vector  $\varphi \neq 0$  such that  $\langle \varphi, X \varphi \rangle = 0$ . Indeed, we can set  $e_1 = \varphi / \|\varphi\|$ , consider  $\varphi^{\perp}$ , the subspace orthogonal to  $\varphi$ , and then repeat the same argument for  $X_1 = P_{\varphi^{\perp}} X|_{\varphi^{\perp}}$ , the operator on

$\varphi^\perp$  obtained by restricting  $X$  to  $\varphi^\perp$  and then projecting the image on  $\varphi^\perp$ :  $X_1$  is still a null trace operator and by induction we can find  $e_2$  and the rest of the basis.

Let us show the existence of  $\varphi$ . Set  $A = (X + X^*)/2$  and  $B = (X - X^*)/2i$  so that  $X = A + iB$ , with  $A$  and  $B$  null trace self-adjoint operators, and consider the eigenbasis  $\{|k\rangle\}$  of  $A = \sum_k a_k |k\rangle\langle k|$ . Then for every  $\varphi \in \mathcal{H}$ ,  $\varphi = \sum_k \varphi_k |k\rangle$ ,

$$\langle \varphi, X \varphi \rangle = \sum_k a_k |\varphi_k|^2 + i \langle \varphi, B \varphi \rangle ,$$

where the first summand vanishes for  $|\varphi_k|$  constant. Therefore, if we consider in  $\mathcal{H}$  the torus of unit vectors

$$\mathcal{T} = \left\{ \varphi \in \mathcal{H} \middle| \varphi_k = \frac{e^{i\theta_k}}{\sqrt{N}}, \quad \theta_k \in [0, 2\pi), \quad k = 1, \dots, N \right\} ,$$

we have that

$$\phi \mapsto \langle \varphi, X \varphi \rangle = i \langle \varphi, B \varphi \rangle = \frac{i}{N} \sum_{\ell, k} e^{-i(\theta_\ell - \theta_k)} \langle \ell | B | k \rangle ,$$

is a purely imaginary valued continuous function on  $\mathcal{T}$ , with average

$$\frac{1}{N} \sum_{\ell, k} (2\pi)^{-N} \int_0^{2\pi} d\theta_1 \dots \int_0^{2\pi} d\theta_N e^{-i(\theta_\ell - \theta_k)} \langle \ell | B | k \rangle = \frac{\text{tr } B}{N} = 0 .$$

Hence there is at least one unit vector  $\varphi \in \mathcal{T}$  such that  $\langle \varphi, X \varphi \rangle = i \langle \varphi, B \varphi \rangle = 0$ .

□

## B. ‘DS’ $\Rightarrow$ ‘Q’

It was already shown in [6] that for qubits the quantum analog of Birkhoff’s Theorem holds. The proof given in that paper was based, however, on a full analysis of the extremal doubly stochastic operators. Here we give a different, more direct proof.

Given a doubly stochastic qubit channel  $T : \mathcal{L}(\mathcal{H}) \rightarrow \mathcal{L}(\mathcal{H})$ , with  $\mathcal{H} = \mathbb{C}^2$  the two dimensional Hilbert space, we have to show that there exist a Kraus representation  $T(\rho) = \sum_\alpha t_\alpha \rho t_\alpha^*$  such that  $t_\alpha$  are all proportional to unitary operators. Let us recall that  $u \in \mathcal{L}(\mathcal{H})$ ,  $\dim \mathcal{H} = 2$ , is unitary if and only if  $u = e^{i\theta}(a_0 \mathbb{1} + i \sum_{j=1}^3 a_j \sigma_j)$  for real  $\theta$ ,  $a_0, \dots, a_3$ , such that  $\sum_j a_j^2 = 1$ . As usual,  $\sigma_j$  denote the Pauli matrices with  $\sigma_0 = \mathbb{1}$ . By expanding all Kraus operators in Pauli matrices we can write the given doubly stochastic channel as

$$T(\rho) = \sum_{i,j=0}^3 R_{ij} \sigma_i \rho \sigma_j ,$$

with some complex  $4 \times 4$ -matrix  $R = (R_{ij})$  enjoying the properties

$$R \geq 0, \quad \text{tr } R = 1, \quad R_{0j} = -R_{j0}, \quad R_{ij} = R_{ji}, \quad \forall i, j = 1, 2, 3. \quad (14)$$

Property  $R \geq 0$  is equivalent to the complete positivity of  $T$ , while the others are equivalent to  $\text{tr } T(\rho) = \text{tr } \rho$  and  $T(\mathbb{1}) = \mathbb{1}$ . We need the following lemma.

**Lemma 7** *Let  $R = (R_{ij})_{i,j=0}^3$  be a  $4 \times 4$  complex matrix enjoying properties (14). Then there exists an orthonormal basis of eigenvectors  $\varphi^{(\alpha)} \in \mathbb{C}^4$  of  $R$  with the first component  $\varphi_0^{(\alpha)} \in \mathbb{R}$  and the other  $\varphi_j^{(\alpha)} \in i\mathbb{R}$ .*

Before proving this lemma, let us verify that it does solve our problem. Indeed, if the  $\varphi^{(\alpha)}$  are such a basis, use the spectral decomposition  $R = \sum_\alpha r_\alpha |\varphi^{(\alpha)}\rangle\langle\varphi^{(\alpha)}|$ ,  $r_\alpha \geq 0$ , to get

$$T(\rho) = \sum_{i,j=0}^3 R_{ij} \sigma_i \rho \sigma_j = \sum_{i,j=0}^3 \sum_{\alpha=0}^3 r_\alpha \varphi_i^{(\alpha)} \bar{\varphi}_j^{(\alpha)} \sigma_i \rho \sigma_j = \sum_{\alpha=0}^3 r_\alpha \left( \sum_{i=0}^3 \varphi_i^{(\alpha)} \sigma_i \right) \rho \left( \sum_{j=0}^3 \bar{\varphi}_j^{(\alpha)} \sigma_j \right) = \sum_{\alpha=0}^3 t_\alpha \rho t_\alpha^* ,$$

where  $t_\alpha = \sqrt{r_\alpha} \left( \sum_{i=0}^3 \varphi_i^{(\alpha)} \sigma_i \right)$  with  $\sum_{i=0}^3 \varphi_i^{(\alpha)} \sigma_i$  unitary.

*Proof.* If we introduce the antiunitary involution  $S : \mathbb{C}^4 \rightarrow \mathbb{C}^4$

$$S \begin{pmatrix} \varphi_0 \\ \varphi_1 \\ \varphi_2 \\ \varphi_3 \end{pmatrix} = \begin{pmatrix} \bar{\varphi}_0 \\ -\bar{\varphi}_1 \\ -\bar{\varphi}_2 \\ -\bar{\varphi}_3 \end{pmatrix},$$

then the conditions (14) on  $R$  become  $R \geq 0$  and  $S \circ R = R \circ S$ , whereas the required property for the eigenvectors  $\varphi$  can be written as  $S\varphi = \varphi$ . Therefore we are given  $S \circ R = R \circ S$  and we are looking for “real”, i.e.  $S$ -invariant, eigenvectors.

Consider any eigenvector  $\varphi$  of  $R$ . Then  $S\varphi$  is an eigenvector for the same eigenvalue. Now we can either have that  $S\varphi$  is proportional to  $\varphi$ , in which case we can adjust the phase to make  $S\varphi = \varphi$ . Or else,  $S\varphi$  and  $\varphi$  are linearly independent, and span a two-dimensional subspace which is invariant under  $S$ , and on which  $R$  acts like a positive multiple of  $\mathbb{1}$ . In this subspace we can again find a basis of  $S$ -invariant vectors. In either case, the orthogonal complement of the subspace generated by  $\varphi$  and  $S\varphi$  is again invariant under both operators, and we continue with the eigenvectors of  $R$  in this complement, thereby constructing successively a basis of  $S$ -invariant eigenvectors.  $\square$

## V. OPTIMAL RECOVERY OF QUANTUM INFORMATION

If quantum information is sent through a ‘not Q’ channel, it is natural in our framework to look for the correction schemes which give the best possible information preserving, i.e. which bring the corrected channel  $T_{\text{corr}}$  (3) as close as possible to  $\text{id}_1$ , in some sense. In this Section we find optimal restoring channels  $R_\alpha$  for a given measurement  $M_\alpha$ . Even if the result leaves unsolved the problem of choosing  $M_\alpha$ , it is interesting by itself for all those situations where practical constraints could prevent the choice of  $M_\alpha$  (which could happen also with a ‘Q’ channel). We define the optimal  $R_\alpha$  to be the channels which maximize the *channel fidelity* of the corrected channel,  $\mathcal{F}(T_{\text{corr}})$ . For a channel  $T : \mathcal{L}(\mathcal{H}) \rightarrow \mathcal{L}(\mathcal{H})$ ,  $T(\rho) = \sum_\alpha t_\alpha \rho t_\alpha^*$ , denoted by  $\Omega$  a maximally entangled unit vector in  $\mathcal{H} \otimes \mathcal{H}$ , the channel fidelity

$$\mathcal{F}(T) = \langle \Omega, T \otimes \text{id}(|\Omega\rangle\langle\Omega|) \Omega \rangle = \frac{1}{(\dim \mathcal{H})^2} \sum_\alpha |\text{tr } t_\alpha|^2$$

measures how well  $T$  preserves quantum information, reaching 1 if and only if  $T = \text{id}$ .

Given  $T : \mathcal{L}(\mathcal{H}_1) \rightarrow \mathcal{L}(\mathcal{H}_2)$ , chosen a Kraus decomposition (5) and the restoring channels  $R_\alpha : \mathcal{L}(\mathcal{H}_2) \rightarrow \mathcal{L}(\mathcal{H}_1)$ ,

$$R_\alpha(\rho') = \sum_\beta r_\beta^\alpha \rho r_\beta^{\alpha*}, \quad \sum_\beta r_\beta^{\alpha*} r_\beta^\alpha = \mathbb{1},$$

we are interested in

$$\mathcal{F}(T_{\text{corr}}) = \frac{1}{(\dim \mathcal{H}_1)^2} \sum_{\alpha, \beta} |\text{tr } r_\beta^\alpha t_\alpha|^2, \quad (15)$$

and we want to maximize it with respect to all possible families  $\{R_\alpha\}$ .

**Proposition 8** *Let  $T : \mathcal{L}(\mathcal{H}_1) \rightarrow \mathcal{L}(\mathcal{H}_2)$  be a channel with a fixed Kraus decomposition (5) and, for every family of channels  $R_\alpha : \mathcal{L}(\mathcal{H}_2) \rightarrow \mathcal{L}(\mathcal{H}_1)$ , let  $T_{\text{corr}} : \mathcal{L}(\mathcal{H}_1) \rightarrow \mathcal{L}(\mathcal{H}_1)$  be the corresponding overall corrected channel (3). Then for every family  $\{R_\alpha\}$*

$$\mathcal{F}(T_{\text{corr}}) \leq \frac{1}{(\dim \mathcal{H}_1)^2} \sum_\alpha \left( \text{tr } |t_\alpha| \right)^2. \quad (16)$$

*Moreover equality can always be attained and it holds if and only if*

$$R_\alpha(\rho') = v_\alpha^* \rho' v_\alpha + \tilde{R}_\alpha(\rho'), \quad \text{where } \tilde{R}_\alpha(t_\alpha \rho t_\alpha^*) = 0 \quad \forall \rho \in \mathcal{L}(\mathcal{H}_1), \quad (17)$$

*or, equivalently, if and only if*

$$T_{\text{corr}}(\rho) = \sum_\alpha |t_\alpha| \rho |t_\alpha|. \quad (18)$$

Before proving the Proposition we write an explicit example of channels (17). To do this, we need to introduce the polar decomposition of the Kraus operators of  $T$ ,

$$t_\alpha = v_\alpha |t_\alpha|, \quad (19)$$

where  $|t_\alpha| = \sqrt{t_\alpha^* t_\alpha} : \mathcal{L}(\mathcal{H}_1) \rightarrow \mathcal{L}(\mathcal{H}_1)$  and  $v_\alpha$  is a partial isometry from  $\text{range}(|t_\alpha|)$  to  $\text{range}(t_\alpha)$  which we extend to an operator from  $\mathcal{H}_1$  to  $\mathcal{H}_2$  by defining it to be 0 on  $\text{range}(|t_\alpha|)^\perp$ . Then  $v_\alpha^* v_\alpha$  is the orthogonal projection on  $\text{range}(|t_\alpha|)$  while  $v_\alpha v_\alpha^*$  is the orthogonal projection on  $\text{range}(t_\alpha)$ . Using  $v_\alpha$  we can satisfy (17) defining the channels

$$R_\alpha(\rho') = v_\alpha^* \rho' v_\alpha + \rho_\alpha \text{tr}(\rho'(\mathbb{1} - v_\alpha v_\alpha^*)) , \quad (20)$$

where  $\rho_\alpha$  are arbitrary density operators in  $\mathcal{L}(\mathcal{H}_1)$ .

*Proof.* Inequality (16) follows from (15) because the Cauchy-Schwarz inequality for the Hilbert-Schmidt inner product gives

$$\sum_\beta |\text{tr} r_\beta^\alpha t_\alpha|^2 = \sum_\beta \left| \text{tr} (r_\beta^\alpha v_\alpha |t_\alpha|^{1/2} |t_\alpha|^{1/2}) \right|^2 \leq \sum_\beta \text{tr} (|t_\alpha|^{1/2} v_\alpha^* r_\beta^\alpha r_\beta^\alpha v_\alpha |t_\alpha|^{1/2}) \text{tr} |t_\alpha| = \left( \text{tr} |t_\alpha| \right)^2. \quad (21)$$

If  $R_\alpha$  are chosen according to (20), then  $T_{\text{corr}}$  is given by (18) and equality holds in (16). And the same is true for every family of restoring channels (17).

Still remaining to prove is that equality in (16) implies (17). Equality holds in (16) if and only if equality holds in (21) for every  $\alpha$ , which occurs if and only if  $r_\beta^\alpha v_\alpha |t_\alpha|^{1/2} = \lambda_{\alpha\beta} |t_\alpha|^{1/2}$ ,  $\lambda_{\alpha\beta} \in \mathbb{C}$ , for every  $\alpha$  and  $\beta$ . Then  $r_\beta^\alpha t_\alpha = \lambda_{\alpha\beta} t_\alpha$  and  $\tilde{R}_\alpha(t_\alpha \rho t_\alpha^*) = R_\alpha(t_\alpha \rho t_\alpha^*) - v_\alpha^* t_\alpha \rho t_\alpha^* v_\alpha = 0$ .  $\square$

The structure of the optimal restoring channels (17) or (20), obtained by maximizing  $\mathcal{F}(T_{\text{corr}})$ , is just what one could expect. When a measurement on the environment has given the result  $\alpha$ , we deal with a subensemble of systems undergone the state transformation  $\rho \mapsto t_\alpha \rho t_\alpha^* = v_\alpha |t_\alpha| \rho |t_\alpha| v_\alpha^*$ , which can be seen as a composition of  $\rho \mapsto |t_\alpha| \rho |t_\alpha|$  followed by  $\rho \mapsto v_\alpha \rho v_\alpha^*$ . Unless we are in the trivial case  $|t_\alpha| \propto \mathbb{1}$ , only the second transformation is physically reversible, and this is just what the channels (17) and (20) do. Notice that if  $|t_\alpha| \propto \mathbb{1}$  then  $T$  is decomposed into isometric channels, the restoring channels (20) coincide with (7), the correction scheme restores quantum information and  $\mathcal{F}(T_{\text{corr}}) = 1$ . As anticipated in Section II C 2, a correction scheme based on channels (17) or (20) not only recovers optimally quantum information, but if the measurement on the environment allows restoring of classical information in a basis  $B$ , i.e. if  $|t_\alpha|$  are diagonal in  $B$ , then it also restores such information.

## VI. MIXED ENVIRONMENTS

When a channel (1) is realised by coupling the system to an environment whose initial state  $\rho_0$  is not pure, the possible decompositions of the channel  $T = \sum_\alpha T_\alpha$  given by a measurement on the environment (see (2)) actually depend on  $\rho_0$ . As a consequence, the possibility of restoring quantum or classical information sent through the channel does not depend only on the channel, but also on the details of the coupling. We will illustrate this feature with an example of a ‘N not S’ depolarizing qubit channel. Since the same channel would be ‘Q’ if the environment were pure, the example shows that a mixed environment can cause the highest possible drop in our hierarchy. Moreover, since it is a qubit channel, it also shows that with mixed environments the special properties of qubits are destroyed.

**Example 8.** Let us consider the channel  $T : \mathcal{L}(\mathcal{H}) \rightarrow \mathcal{L}(\mathcal{H})$  arising from coupling a qubit, of Hilbert space  $\mathcal{H}$ , to another qubit, the environment, of Hilbert space  $\mathcal{K}$  and initial state  $\rho_0 = \mathbb{1}/2$ , by the interaction  $U$

$$U \chi_1 \otimes \xi_1 = \psi_1 \otimes \eta_1, \quad U \chi_1 \otimes \xi_0 = \psi_0 \otimes \zeta_1, \quad U \chi_0 \otimes \xi_1 = \psi_1 \otimes \eta_0, \quad U \chi_0 \otimes \xi_0 = \psi_0 \otimes \zeta_0,$$

where  $\{\chi_x\} \subset \mathcal{H}$ ,  $\{\psi_x\} \subset \mathcal{H}$ ,  $\{\xi_x\} \subset \mathcal{K}$ , and  $\{\eta_x\} \subset \mathcal{K}$  are arbitrary orthonormal bases. The coupling is non-trivial, because it contains yet another basis  $\{\zeta_x\} \subset \mathcal{K}$ , explicitly given by

$$\zeta_1 = \frac{\eta_1 + \eta_0}{\sqrt{2}}, \quad \zeta_0 = \frac{\eta_1 - \eta_0}{\sqrt{2}}.$$

Then it is easy to verify that (1) gives the depolarizing channel  $T(\rho) = \mathbb{1}/2$ . But, even if the evolution  $U$  is followed by the measurement on the second qubit of an observable  $M_\alpha = |\mu_\alpha\rangle\langle\mu_\alpha|$ , for some complete system  $\{\mu_\alpha\}$  in  $\mathcal{K}$ ,

anyhow the classical information sent through this channel is lost, for every choice of the encoding basis  $B$ : the (non normalized) states  $T_\alpha(B_1)$  and  $T_\alpha(B_0)$  are always non orthogonal and hence no channel  $R_\alpha$  can distinguish them and restore the initial states. Indeed, for every basis  $B = \{\varphi_x\}$  in  $\mathcal{H}$ ,

$$\begin{aligned} U \varphi_1 \otimes \xi_1 &= \psi_1 \otimes \left( \langle \chi_1, \varphi_1 \rangle \eta_1 + \langle \chi_0, \varphi_1 \rangle \eta_0 \right) = \psi_1 \otimes \tilde{\eta}_1, & U \varphi_1 \otimes \xi_0 &= \psi_0 \otimes \left( \langle \chi_1, \varphi_1 \rangle \zeta_1 + \langle \chi_0, \varphi_1 \rangle \zeta_0 \right) = \psi_0 \otimes \tilde{\zeta}_1, \\ U \varphi_0 \otimes \xi_1 &= \psi_1 \otimes \left( \langle \chi_1, \varphi_0 \rangle \eta_1 + \langle \chi_0, \varphi_0 \rangle \eta_0 \right) = \psi_1 \otimes \tilde{\eta}_0, & U \varphi_0 \otimes \xi_0 &= \psi_0 \otimes \left( \langle \chi_1, \varphi_0 \rangle \zeta_1 + \langle \chi_0, \varphi_0 \rangle \zeta_0 \right) = \psi_0 \otimes \tilde{\zeta}_0, \end{aligned}$$

where  $\{\tilde{\eta}_x\}$  and  $\{\tilde{\zeta}_x\}$  are two bases in  $\mathcal{K}$  such that

$$\tilde{\zeta}_1 = \frac{\tilde{\eta}_1 + \tilde{\eta}_0}{\sqrt{2}}, \quad \tilde{\zeta}_0 = \frac{\tilde{\eta}_1 - \tilde{\eta}_0}{\sqrt{2}},$$

and so

$$T_\alpha(|\varphi_x\rangle\langle\varphi_x|) = \text{tr}_{\mathcal{K}} \left( U (|\varphi_x\rangle\langle\varphi_x| \otimes \frac{\mathbb{1}}{2}) U^* (\mathbb{1} \otimes |\mu_\alpha\rangle\langle\mu_\alpha|) \right) = \frac{1}{2} \left\{ |\psi_1\rangle\langle\psi_1| \cdot |\langle\tilde{\eta}_x, \mu_\alpha\rangle|^2 + |\psi_0\rangle\langle\psi_0| \cdot |\langle\tilde{\zeta}_x, \mu_\alpha\rangle|^2 \right\},$$

where at most one of the coefficients  $|\langle\tilde{\eta}_1, \mu_\alpha\rangle|^2$ ,  $|\langle\tilde{\eta}_0, \mu_\alpha\rangle|^2$ ,  $|\langle\tilde{\zeta}_1, \mu_\alpha\rangle|^2$ ,  $|\langle\tilde{\zeta}_0, \mu_\alpha\rangle|^2$  can vanish so that  $T_\alpha(|\varphi_1\rangle\langle\varphi_1|)$  and  $T_\alpha(|\varphi_0\rangle\langle\varphi_0|)$  are never orthogonal and  $T$  is not ‘S’.

## VII. ANALYSIS WITH LOCC OPERATIONS

Our correction scheme was motivated by situations where the measurement on the environment and subsequent recovery are realized by physical processes, possibly to be run repeatedly, or even in continuous time. Therefore we did not incorporate a possible dependence of the whole process on information previously gained on the system. On the other hand, the ‘lost and found’ scenario might well be extended to contain such dependences. The most general case would then maybe begin with a quantum measurement on the system, to ascertain the losses. Based on that information a classical call would be made to the Lost and Found Office in the environment. An employee would then make a quantum measurement on the shelves in the office, maybe ask a question for more classical information about the system, and so on. All this amounts to a cooperation between the system manager and the Lost and Found employee, in the framework of an LOCC (‘Local quantum operations and classical communication’) protocol [13]. Developing the corrigibility criteria for such protocols is beyond the present work. Therefore we only give one example showing that the extended framework does make a difference in some situations.

We consider Example 8 of Section VI, where classical information encoded on the first qubit can never be retrieved after the interaction by our correction scheme. The simple LOCC scheme, which will achieve correction in this case is to start with a measurement on the ‘system’ qubit followed by a suitable measurement on the ‘environment’ qubit, chosen according to the first result.

Fix the encoding basis  $B = \{\varphi_x\}$  in  $\mathcal{H}$ , the corresponding bases  $\{\tilde{\eta}_x\}$  and  $\{\tilde{\zeta}_x\}$  are fixed in  $\mathcal{K}$ , too, and the initial state of the bipartite system is one of the  $|\varphi_x\rangle\langle\varphi_x| \otimes \mathbb{1}/2$ ,  $x = 1, 0$ . After the interaction  $U$  we measure on the first qubit  $F_\alpha = |\psi_\alpha\rangle\langle\psi_\alpha| \in \mathcal{L}(\mathcal{H})$  so that, according to the result  $\alpha$  and the classical information  $x$ , the subsequent (non normalized) state of the second qubit is

$$\tilde{\rho}_\alpha(x) = \text{tr}_{\mathcal{H}} \left( U (|\varphi_x\rangle\langle\varphi_x| \otimes \frac{\mathbb{1}}{2}) U^* (|\psi_\alpha\rangle\langle\psi_\alpha| \otimes \mathbb{1}) \right) = \frac{1}{2} |\tilde{\xi}_x^{(\alpha)}\rangle\langle\tilde{\xi}_x^{(\alpha)}|, \quad \text{where } \tilde{\xi}_x^{(\alpha)} = \begin{cases} \tilde{\eta}_x, & \alpha = 1, \\ \tilde{\zeta}_x, & \alpha = 0. \end{cases}$$

Therefore  $\tilde{\rho}_\alpha(1)$  and  $\tilde{\rho}_\alpha(0)$  are orthogonal for every  $\alpha$  and classical information can be recovered by a measurement of  $\{\tilde{\xi}_x^{(\alpha)}\}_x$ .

**Acknowledgements.** M.G. gratefully acknowledges support from the Alexander von Humboldt Foundation. Our work was also supported by the European Union project EQUIP (contract IST-1999-11053) and the DFG (Bonn).

---

[1] E. B. Davies: Quantum theory of open system (Academic Press, London, 1976)

[2] M.A. Nielsen and I.L. Chuang: Quantum computation and quantum information (Cambridge UP, Cambridge 2000)

- [3] M. Keyl, R.F. Werner: How to correct small quantum errors. To appear in: A. Buchleitner and K. Hornberger (eds.), *Coherent Evolution in Noisy Environment*, Lecture Notes in Physics, Springer (2002); preprint quant-ph/0206086;
- [4] G. Alber, Th. Beth, Ch. Charnes, A. Delgado, M. Grassl, M. Mussinger: Stabilizing distinguishable qubits against spontaneous decay by detected-jump correcting quantum codes. *Phys. Rev. Lett.* **86** No. 19, 4402-4405 (2001)
- [5] M. B. Plenio, V. Vedral, P. L. Knight: Quantum error correction in the presence of spontaneous emission. *Phys. Rev. A* **55**, 67-71 (1997)
- [6] L. J. Landau, R. F. Streater: On Birkhoff's theorem for doubly stochastic completely positive maps of matrix algebras. *J. Linear Alg. Appl.* **193**, 107-127 (1993)
- [7] H. Maassen, B. Kümmerer: The essentially commutative dilations of dynamical semigroups on  $M_n$ . *Commun. Math. Phys.* **109**(1987)1-22; see especially the remark after Proposition 2.2.1.
- [8] R.F. Werner: All Teleportation and Dense Coding Schemes. *J. Phys. A* **35** (2001) 7081-7094 or quant-ph/0003070
- [9] A. O. Barut, R. Raczyk: *Theory of Group Representations and Applications* (World Scientific Publishing, Singapore, 1986)
- [10] A.S. Holevo, R.F. Werner: Counterexample to an additivity conjecture for output purity of quantum channels. To appear in *J.Math.Phys.* (2002), see quant-ph/0203003
- [11] V. Buzek, M. Hillery, R.F. Werner: Optimal Manipulations with Qubits: Universal NOT Gate. *Phys. Rev. A* **60**, R2626 (1999) or quant-ph/9901053
- [12] J. Walgate, A. J. Short, L. Hardy, V. Vedral: Local distinguishability of multipartite orthogonal quantum states. *Phys. Rev. Lett.* **85**, 4972 (2000)
- [13] C. Bennett, H. Bernstein, S. Popescu, B. Schumacher: Concentrating partial entanglement by local operations, *Phys Rev A* **53** (1996) 2046, or quant-ph/9511030.